



Condor Technology Ltd.

DATASHEET: ELECTRICAL SMART-SPACE HEATER, GENERAL PURPOSE MODEL GSMLP-(*)A



1 Application

Space-heaters for Non-Hazardous locations, designed for

- Anti-condensation
- Freeze protection
- Temperature maintenance

2 Features and Advantages

- Self-limiting heating elements
- Small dimensions
- No moving parts, no maintenance required, therefore long lifetime
- Can be used for 110 / 240 VAC/DC

3 Description

All SMART Space-Heaters are designed around self-limiting heating elements. These semiconductor elements are saving power consumption.

Our SMART Space-Heaters are designed to heat the air inside an enclosure and indirectly the installed equipment. If properly selected for freeze protection, no thermostat will be needed.

When required in other applications, e.g. analyzers, it is normal practice to use our SMART Space-Heaters in combination with our Fix-Therm96 thermostats (range from 10°C up to 130°C).



4 Range

GSMLP-1A	T3	ca. 115°C Surface temperature	100-10 Watt
GSMLP-2A	T4	ca. 105°C Surface temperature	100-10 Watt
GSMLP-3A	T4	ca. 90°C Surface temperature	100-10 Watt
GSMLP-4A	T4	ca. 70°C Surface temperature	100-10 Watt

High power model:

GSMLP-0AHP	T3	ca. 130°C Surface temperature	200-20 Watt
------------	----	-------------------------------	-------------

* these temperatures are measured at 20°C ambient temperature.

5 Technical data

Power consumption	:	100-10 Watt or 200-20 Watt
Electrical cable	:	3 x 1 sqmm
Material cable	:	Non-braided silicone cable
Standard length	:	Ca. 1 mtr., other lengths optional
Other lengths	:	To be specified
Weight	:	Ca. 1400 g.
Overall dimensions	:	100 x 54 x 54 mm (LxWxH)
Material	:	Black anodized aluminium
Voltage AC/DC	:	110/240



Condor Technology Ltd.



Copyright © Condor Technology Ltd. all rights reserved.



The information contained herein is believed to be reliable. Condor Technology Ltd. assumes no responsibility or liability whatsoever for any of the information contained herein.



Condor Technology Ltd.

Copyright © Condor Technology Ltd. all rights reserved.



The information contained herein is believed to be reliable. Condor Technology Ltd. assumes no responsibility or liability whatsoever for any of the information contained herein.